



**MICROCHIP**

---

**MCP19035**  
**300 kHz Synchronous**  
**Buck Controller**  
**Evaluation Board**  
**User's Guide**

---

**Note the following details of the code protection feature on Microchip products:**

- Microchip products meet the specifications contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is secure when used in the intended manner, within operating specifications, and under normal conditions.
- Microchip values and aggressively protects its intellectual property rights. Attempts to breach the code protection features of Microchip product is strictly prohibited and may violate the Digital Millennium Copyright Act.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of its code. Code protection does not mean that we are guaranteeing the product is “unbreakable”. Code protection is constantly evolving. Microchip is committed to continuously improving the code protection features of our products.

---

This publication and the information herein may be used only with Microchip products, including to design, test, and integrate Microchip products with your application. Use of this information in any other manner violates these terms. Information regarding device applications is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. Contact your local Microchip sales office for additional support or, obtain additional support at <https://www.microchip.com/en-us/support/design-help/client-support-services>.

THIS INFORMATION IS PROVIDED BY MICROCHIP "AS IS". MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE, OR WARRANTIES RELATED TO ITS CONDITION, QUALITY, OR PERFORMANCE.

IN NO EVENT WILL MICROCHIP BE LIABLE FOR ANY INDIRECT, SPECIAL, PUNITIVE, INCIDENTAL, OR CONSEQUENTIAL LOSS, DAMAGE, COST, OR EXPENSE OF ANY KIND WHATSOEVER RELATED TO THE INFORMATION OR ITS USE, HOWEVER CAUSED, EVEN IF MICROCHIP HAS BEEN ADVISED OF THE POSSIBILITY OR THE DAMAGES ARE FORESEEABLE. TO THE FULLEST EXTENT ALLOWED BY LAW, MICROCHIP'S TOTAL LIABILITY ON ALL CLAIMS IN ANY WAY RELATED TO THE INFORMATION OR ITS USE WILL NOT EXCEED THE AMOUNT OF FEES, IF ANY, THAT YOU HAVE PAID DIRECTLY TO MICROCHIP FOR THE INFORMATION.

Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights unless otherwise stated.

For information regarding Microchip's Quality Management Systems, please visit [www.microchip.com/quality](http://www.microchip.com/quality).

**Trademarks**

The Microchip name and logo, the Microchip logo, Adaptec, AnyRate, AVR, AVR logo, AVR Freaks, BesTime, BitCloud, CryptoMemory, CryptoRF, dsPIC, flexPWR, HELDO, IGLOO, JukeBlox, KeeLoq, Kleer, LANCheck, LinkMD, maxStylus, maXTouch, MediaLB, megaAVR, Microsemi, Microsemi logo, MOST, MOST logo, MPLAB, OptoLyzer, PIC, picoPower, PICSTART, PIC32 logo, PolarFire, Prochip Designer, QTouch, SAM-BA, SenGenuity, SpyNIC, SST, SST Logo, SuperFlash, Symmetricom, SyncServer, Tachyon, TimeSource, tinyAVR, UNI/O, Vectron, and XMEGA are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

AgileSwitch, APT, ClockWorks, The Embedded Control Solutions Company, EtherSynch, Flashtec, Hyper Speed Control, HyperLight Load, IntelliMOS, Libero, motorBench, mTouch, Powermite 3, Precision Edge, ProASIC, ProASIC Plus, ProASIC Plus logo, QuietWire, SmartFusion, SyncWorld, Temux, TimeCesium, TimeHub, TimePictra, TimeProvider, TrueTime, WinPath, and ZL are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Adjacent Key Suppression, AKS, Analog-for-the-Digital Age, Any Capacitor, AnyIn, AnyOut, Augmented Switching, BlueSky, BodyCom, CodeGuard, CryptoAuthentication, CryptoAutomotive, CryptoCompanion, CryptoController, dsPICDEM, dsPICDEM.net, Dynamic Average Matching, DAM, ECAN, Espresso T1S, EtherGREEN, GridTime, IdealBridge, In-Circuit Serial Programming, ICSP, INICnet, Intelligent Paralleling, Inter-Chip Connectivity, JitterBlocker, Knob-on-Display, maxCrypto, maxView, memBrain, Mindi, MiWi, MPASM, MPF, MPLAB Certified logo, MPLIB, MPLINK, MultiTRAK, NetDetach, NVM Express, NVMe, Omniscient Code Generation, PICDEM, PICDEM.net, PICkit, PICTail, PowerSmart, PureSilicon, QMatrix, REAL ICE, Ripple Blocker, RTAX, RTG4, SAM-ICE, Serial Quad I/O, simpleMAP, SimpliPHY, SmartBuffer, SmartHLS, SMART-I.S., storClad, SQL, SuperSwitcher, SuperSwitcher II, Switchtec, SynchroPHY, Total Endurance, TSHARC, USBCheck, VariSense, VectorBlox, VeriPHY, ViewSpan, WiperLock, XpressConnect, and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

The Adaptec logo, Frequency on Demand, Silicon Storage Technology, Symmcom, and Trusted Time are registered trademarks of Microchip Technology Inc. in other countries.

GestIC is a registered trademark of Microchip Technology Germany II GmbH & Co. KG, a subsidiary of Microchip Technology Inc., in other countries.

All other trademarks mentioned herein are property of their respective companies.

© 2012-2022, Microchip Technology Incorporated and its subsidiaries.

All Rights Reserved.

ISBN: 978-1-6683-0314-6



# MCP19035 300 KHZ SYNCHRONOUS BUCK CONTROLLER EVALUATION BOARD USER'S GUIDE

## Table of Contents

<b>Preface</b> .....	<b>5</b>
Introduction.....	5
Document Layout .....	5
Conventions Used in this Guide .....	6
Recommended Reading.....	7
The Microchip Web Site .....	7
Customer Support .....	7
Document Revision History .....	7
<b>Chapter 1. Product Overview</b>	
1.1 Introduction .....	9
1.2 Short Overview: MCP19035 .....	9
1.3 What Is the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board? .....	10
1.4 What the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board Kit Contains .....	10
<b>Chapter 2. Installation and Operation</b>	
2.1 Introduction .....	11
2.2 Getting Started .....	11
2.2.1 Necessary Instruments and Tools .....	11
2.2.2 Setup Procedure .....	11
2.2.3 Board Testing .....	12
<b>Appendix A. Schematic and Layouts</b>	
A.1 Introduction .....	15
A.2 Board – Schematic .....	16
A.3 Board – Top Silk and Pads .....	17
A.4 Board – Top Copper and Silk .....	18
A.5 Board – Top Copper .....	19
A.6 Board – Mid Layer 1 .....	20
A.7 Board – Mid Layer 2 .....	21
A.8 Board – Bottom Copper and Pads .....	22
A.9 Board – Bottom Copper, Silk and Pads .....	23
A.10 Board – Bottom Silk .....	24
<b>Appendix B. Bill of Materials</b>	
<b>Appendix C. Typical Performance Data, Curves and Waveforms</b>	
C.1 Introduction .....	27
<b>Worldwide Sales and Service</b> .....	<b>34</b>

**NOTES:**



# MCP19035 300 KHZ SYNCHRONOUS BUCK CONTROLLER EVALUATION BOARD USER'S GUIDE

## Preface

### NOTICE TO CUSTOMERS

All documentation becomes dated, and this manual is no exception. Microchip tools and documentation are constantly evolving to meet customer needs, so some actual dialogs and/or tool descriptions may differ from those in this document. Please refer to our web site ([www.microchip.com](http://www.microchip.com)) to obtain the latest documentation available.

Documents are identified with a “DS” number. This number is located on the bottom of each page, in front of the page number. The numbering convention for the DS number is “DSXXXXA”, where “XXXX” is the document number and “A” is the revision level of the document.

For the most up-to-date information on development tools, see the MPLAB® IDE online help. Select the Help menu, and then Topics to open a list of available online help files.

## INTRODUCTION

This chapter contains general information that will be useful to know before using the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board. Items discussed in this chapter include:

- Document Layout
- Conventions Used in this Guide
- Recommended Reading
- The Microchip Web Site
- Customer Support
- Document Revision History

## DOCUMENT LAYOUT

This document describes how to use the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board as a development tool to emulate and debug firmware on a target board. The manual layout is as follows:

- **Chapter 1. “Product Overview”** – Shows a brief description of the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board
- **Chapter 2. “Installation and Operation”** – Includes instructions on how to get started with the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board
- **Appendix A. “Schematic and Layouts”** – Shows the schematic and layout diagrams for the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board
- **Appendix B. “Bill of Materials”** – Lists the parts used to build the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board
- **Appendix C. “Typical Performance Data, Curves and Waveforms”** – Shows the typical performance graphs

## CONVENTIONS USED IN THIS GUIDE

This manual uses the following documentation conventions:

### DOCUMENTATION CONVENTIONS

Description	Represents	Examples
<b>Arial font:</b>		
Italic characters	Referenced books	<i>MPLAB® IDE User's Guide</i>
	Emphasized text	...is the <i>only</i> compiler...
Initial caps	A window	the Output window
	A dialog	the Settings dialog
	A menu selection	select Enable Programmer
Quotes	A field name in a window or dialog	"Save project before build"
Underlined, italic text with right angle bracket	A menu path	<u>File</u> > <i>Save</i>
Bold characters	A dialog button	Click <b>OK</b>
	A tab	Click the <b>Power</b> tab
N'Rnnnn	A number in verilog format, where N is the total number of digits, R is the radix and n is a digit.	4'b0010, 2'hF1
Text in angle brackets < >	A key on the keyboard	Press <Enter>, <F1>
<b>Courier New font:</b>		
Plain Courier New	Sample source code	#define START
	Filenames	autoexec.bat
	File paths	c:\mcc18\h
	Keywords	_asm, _endasm, static
	Command-line options	-Opa+, -Opa-
	Bit values	0, 1
	Constants	0xFF, 'A'
Italic Courier New	A variable argument	<i>file.o</i> , where <i>file</i> can be any valid filename
Square brackets [ ]	Optional arguments	mcc18 [options] <i>file</i> [options]
Curly brackets and pipe character: {   }	Choice of mutually exclusive arguments; an OR selection	errorlevel {0 1}
Ellipses...	Replaces repeated text	var_name [, var_name...]
	Represents code supplied by user	void main (void) { ... }

## RECOMMENDED READING

This user's guide describes how to use MCP19035 300 kHz Synchronous Buck Controller Evaluation Board. Other useful documents are listed below. The following Microchip documents are available and recommended as supplemental reference resources.

- **MCP19035 Data Sheet – “High-Speed Synchronous Buck Controller” (DS22326)**
- **AN1452 – “Using the MCP19035 Synchronous Buck Converter Design Tool” (DS01452)**

## THE MICROCHIP WEB SITE

Microchip provides online support via our web site at [www.microchip.com](http://www.microchip.com). This web site is used as a means to make files and information easily available to customers. Accessible by using your favorite Internet browser, the web site contains the following information:

- **Product Support** – Data sheets and errata, application notes and sample programs, design resources, user's guides and hardware support documents, latest software releases and archived software
- **General Technical Support** – Frequently Asked Questions (FAQs), technical support requests, online discussion groups, Microchip consultant program member listing
- **Business of Microchip** – Product selector and ordering guides, latest Microchip press releases, listing of seminars and events, listings of Microchip sales offices, distributors and factory representatives

## CUSTOMER SUPPORT

Users of Microchip products can receive assistance through several channels:

- Distributor or Representative
- Local Sales Office
- Field Application Engineer (FAE)
- Technical Support

Customers should contact their distributor, representative or field application engineer (FAE) for support. Local sales offices are also available to help customers. A listing of sales offices and locations is included in the back of this document.

Technical support is available through the web site at:  
<http://www.microchip.com/support>

## DOCUMENT REVISION HISTORY

### Revision B (April 2022)

- Updated [Appendix A. “Schematic and Layouts”](#).
- Updated [Appendix B. “Bill of Materials”](#).
- Minor format changes throughout.

### Revision A (November 2012)

- Initial Release of this Document.

NOTES:





# MCP19035 300 KHZ SYNCHRONOUS BUCK CONTROLLER EVALUATION BOARD USER'S GUIDE

---

---

## Chapter 1. Product Overview

---

---

### 1.1 INTRODUCTION

This chapter provides an overview of the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board, and covers the following topics:

- [Short Overview: MCP19035](#)
- [What Is the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board?](#)
- [What the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board Kit Contains](#)

### 1.2 SHORT OVERVIEW: MCP19035


The MCP19035 is a highly-featured, highly-integrated, Synchronous Buck Controller in a space-saving 10-pin DFN 3 x 3 mm package, that operates from input voltage sources up to 30V. Integrated features include high and low-side MOSFET drivers, fixed-frequency voltage mode control, internal oscillator and reference voltage generator, overcurrent protection on both the high- and low-side devices, Power Good circuit and overtemperature protection. A minimal number of external components are necessary to develop a complete, high-performance Synchronous Buck Converter power supply.

The MCP19035 Synchronous Buck Controller is intended to be used for applications requiring medium to high-output currents (up to 20A) and input voltages up to 30V.

Typical applications include:

- Medium current Point-of-Load converters
- FPGA/DSP power supplies
- Digital Set-Top boxes
- Industrial 24V rails converters

The internal linear voltage regulator (LDO) allows low current loads (for example, PIC microcontrollers) to be powered directly from this controller without any additional components.



**FIGURE 1-1:** Typical Application.

## 1.3 WHAT IS THE MCP19035 300 KHZ SYNCHRONOUS BUCK CONTROLLER EVALUATION BOARD?

The MCP19035 300 kHz Synchronous Buck Controller Evaluation Board is a compact, highly efficient, step-down voltage regulator that will convert the input voltage rail (typically 12V) to 1.8V regulated output voltage. The maximum output current for this step-down converter is 15A. The board demonstrates the capabilities of the MCP19035 300 kHz synchronous buck converter, as well as Microchip's high-performance power MOSFET transistors. Test points for various signals are provided for measuring different parameters of the converter. The evaluation board can be modified to support output voltages from 0.9V to 3.3V by changing a single resistor.

## 1.4 WHAT THE MCP19035 300 KHZ SYNCHRONOUS BUCK CONTROLLER EVALUATION BOARD KIT CONTAINS

The MCP19035 300 kHz Synchronous Buck Controller Evaluation Board kit includes:

- MCP19035 300 kHz Synchronous Buck Controller Evaluation Board (ADM00434)
- Important Information Sheet

---

---

## Chapter 2. Installation and Operation

---

---

### 2.1 INTRODUCTION

The MCP19035 300 kHz Synchronous Buck Controller Evaluation Board was developed to provide a compact, low-cost and highly efficient step-down conversion for low to medium output currents.

The key features of this board include:

- Input Voltage Range: 8V to 14V
- Output Voltage: 1.8V (can be adjusted by changing one resistor between 0.9V and 3.3V)
- Maximum Output Current: 15A
- 91% typical efficiency at 1.8V/15A output and 12V input
- 300 kHz fixed switching frequency
- On-board High Performance Power MOSFET Transistors
- Overcurrent Protection for High and Low-Side MOSFETs
- Power Good (PGOOD) output for monitoring the output voltage quality
- Shutdown input for placing the converter in a low-power Standby mode
- Under Voltage Lockout (UVLO) with 4.2V and 3.6V (typical) thresholds

### 2.2 GETTING STARTED

The MCP19035 300 kHz Synchronous Buck Controller Evaluation Board is fully assembled and tested to evaluate and demonstrate the MCP19035 capabilities.

#### 2.2.1 Necessary Instruments and Tools

The list of required instruments and tools include:

- Adjustable DC power supply with 0V – 15V/5 A<sub>DC</sub> range output capability
- Electronic load with at least 25A current capability and load stepping capability
- Digital oscilloscope with a minimum bandwidth of 50 MHz
- Digital voltmeter/ammeter
- Optionally, a Network Analyzer/Bode Plot Analyzer for loop analysis
- Wires for connections: they must sustain high current, 5A for the connection between adjustable DC power supply and board, 15A for the connection between board and the electronic load

#### 2.2.2 Setup Procedure


To power-up the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board, the following steps must be completed:

1. Connect the Electronic Load to J2 connector of the demo board; the positive (+) and negative (-) connector pins are marked on the board silkscreen.
2. Connect the Adjustable DC Power Supply to J1 connector on the demo board; the positive (+) and negative (-) connector pins are marked on the board silkscreen.
3. The DC voltage supplied by the Adjustable DC Power Supply should be 12V.

## 2.2.3 Board Testing

The typical test setup is depicted in Figure 2-1. Table 2-1 shows all the available test points on the board.

The user can connect various instruments at the listed test points to evaluate the parameters of the converter. The typical performance data, curves and waveforms are shown in [Appendix C. “Typical Performance Data, Curves and Waveforms”](#).



**FIGURE 2-1:** Typical Test Setup.

**TABLE 2-1: TEST POINTS DESCRIPTION**

Test Point	Label	Description
TP1, TP8, TP12, TP15	GND	Power GND
TP7, TP16, TP19	SGND	Signal GND
TP2	$V_{IN}$	Input voltage
TP3	SHDN	Shutdown input pull-up resistor
TP4	SHDN	Shutdown input
TP5	PGOOD	Power Good output
TP6	EXTPGOOD	External Pull-up for PGOOD signal
TP9	HIGHDR	High-Side MOSFET drive signal
TP10	LOWDR	Low-Side MOSFET drive signal
TP11	SW	Main switch node
TP13	PREBIAS	Pre-bias load point
TP14	$V_{OUT}$	Output Voltage
TP17, TP18	CH A, CH B	Signal Injection points for loop measurement

## 2.2.3.1 ADJUSTING THE OUTPUT VOLTAGE

The output voltage can be modified by changing the value of R12 from the feedback divider. The output voltage is set according to Equation 2-1.

### EQUATION 2-1: OUTPUT VOLTAGE

$$V_{OUT} = V_{REF} \times \frac{R11 + R12}{R12}$$

Where:

$$V_{REF} = 0.6V$$

$$R11 = 20 \text{ k}\Omega$$

Do not modify the value of the R11 resistor (20 k $\Omega$ ), as this will affect the system's loop compensation.

Some parameters, including efficiency, overcurrent protection thresholds, and input and output voltage ripple, can be affected by the modification of the output voltage.

Table 2-2 shows the standard values of R12 resistor for some usual output voltages.

**TABLE 2-2: OUTPUT VOLTAGE VERSUS R12 VALUE**

V <sub>OUT</sub> (V)	R12 (k $\Omega$ )
0.9	40.2
1	30
1.2	20
1.5	13.3
1.8	10
2	8.45
2.25	7.32
2.5	6.34
3.3	4.42

NOTES:



# MCP19035 300 KHZ SYNCHRONOUS BUCK CONTROLLER EVALUATION BOARD USER'S GUIDE

---

---

## Appendix A. Schematic and Layouts

---


---

### A.1 INTRODUCTION

This appendix contains the following schematics and layouts for the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board:

- [Board – Schematic](#)
- [Board – Top Silk and Pads](#)
- [Board – Top Copper and Silk](#)
- [Board – Top Copper](#)
- [Board – Mid Layer 1](#)
- [Board – Mid Layer 2](#)
- [Board – Bottom Copper and Pads](#)
- [Board – Bottom Copper, Silk and Pads](#)
- [Board – Bottom Silk](#)

## A.2 BOARD – SCHEMATIC



Revision History				
Rev.	ECO	Description	Date	Approved




Drawn	Sergiu Oprea	Date	02-03-2011
Checked		Date	
Approved		Date	
Approved		Date	
Approved		Date	


Title			Rev.
MCP19035 300kHz Evaluation Board			3
Size	Doc. Number		
B	103-00434		




## A.3 BOARD – TOP SILK AND PADS




A.4 BOARD – TOP COPPER AND SILK




## A.5 BOARD – TOP COPPER




A.6 BOARD – MID LAYER 1




## A.7 BOARD – MID LAYER 2




A.8 BOARD – BOTTOM COPPER AND PADS



## A.9 BOARD – BOTTOM COPPER, SILK AND PADS



A.10 BOARD – BOTTOM SILK







# MCP19035 300 KHZ SYNCHRONOUS BUCK CONTROLLER EVALUATION BOARD USER'S GUIDE

## Appendix B. Bill of Materials

**TABLE B-1: BILL OF MATERIALS (BOM)**

Qty	Reference	Description	Manufacturer	Part Number
2	C1, C3	CAP CER 22uF 25V 10% X7R 1210	Murata Electronics®	GRM32ER71E226KE15L
1	C2	CAP CER 10UF 25V 10% X7R 1210	TDK Corporation	C3225X7R1E106K
1	C4	CAP CER 6800PF 50V 5% NP0 0603	KEMET	C0603C682J5GACTU
1	C5	CAP CER 0.33UF 16V 10% X7R 0603	Murata Electronics North America, Inc.	GRM188R71C334KA01D
3	C6, C7, C8	CAP CER 100uF 10V 20% X5R SMD 1210	Samsung Electro-Mechanics America, Inc.	CL32A107MPVNNNE
2	C9, C11	CAP CER 1UF 35V 10% X7R 0805	TDK Corporation	CGA4J3X7R1V105K
1	C10	CAP CER 68PF 100V 5% NP0 0603	KEMET	C0603C680J1GACTU
1	C12	CAP CER 4.7UF 25V X5R 0805	TDK Corporation	C2012X5R1E475K
1	C13	CAP CER 820PF 50V 5% NP0 0603	KEMET	C0603C821J5GACTU
1	D1	DIODE SCHOTTKY 0.5A 30V SOD323	Diodes Incorporated®	B0530WS-7-F
2	J1, J2	TERMINAL BLOCK 5.08MM VERT 2POS	On-Shore Technology, Inc.	ED120/2DS
1	L1	INDUCTOR POWER 1.5UH 19.5A SMD	Würth Elektronik	7443320150
1	PCB	MCP19035 300 kHz Synchronous Buck Controller Evaluation Board - Printed Circuit Board	—	04-10120-R3
2	Q1, Q2	TRANS FET N-CH SIRA10BDP-T1-GE3 30V 60A 43W PPAK SO-8	Vishay Siliconix	SIRA10BDP-T1-GE3
1	Q3	MOSFET N-Ch. 60V 115 MA SOT-23-3	Diodes Incorporated	2N7002-7-F
3	R1, R8, R9	RES 5.1k Ohm 1/10W 1% 0603 SMD	Panasonic® - ECG	ERJ-3EKF5101V
2	R2, R7	RES 100k Ohm 1/10W 1% 0603 SMD	Panasonic® - ECG	ERJ-3EKF1003V
1	R3	RES 0 Ohm 1/10W 0603 SMD	Panasonic® - ECG	ERJ-3GEY0R00V
1	R4	RES 100 Ohm 1/10W 1% 0603 SMD	Panasonic® - ECG	ERJ-3EKF1000V
1	R5	RES 7.50K OHM 1/10W 1% 0603 SMD	Panasonic® - ECG	ERJ-3EKF7501V
1	R6	RES 3.3 OHM 1/10W 1% 0603	Panasonic® - ECG	ERJ-3RQF3R3V
1	R10	RES 49.9 OHM .25W 1% 0603 SMD	Vishay/Dale	CRCW060349R9FKEAHP
1	R11	RES 20k Ohm 1/10W 1% 0603 SMD	Panasonic® - ECG	ERJ-3EKF2002V
2	R12, R14	RES 10k Ohm 1/10W 1% 0603 SMD	Panasonic® - ECG	ERJ-3EKF1002V
1	R13	RES 750 OHM 1/10W 1% 0603 SMD	Vishay/Dale	CRCW0603750RFKEA

**Note 1:** The components listed in this Bill of Materials are representative of the PCB assembly. The released BOM used in manufacturing uses all RoHS-compliant components.

**TABLE B-1: BILL OF MATERIALS (BOM) (CONTINUED)**

Qty	Reference	Description	Manufacturer	Part Number
19	TP1, TP2, TP3, TP4, TP5, TP6, TP7, TP8, TP9, TP10, TP11, TP12, TP13, TP14, TP15, TP16, TP17, TP18, TP19	TEST POINT PC MULTI PURPOSE BLK	Keystone® Electronics Corp.	5011

**Note 1:** The components listed in this Bill of Materials are representative of the PCB assembly. The released BOM used in manufacturing uses all RoHS-compliant components.

**TABLE B-2: BILL OF MATERIALS (BOM) – MICROCHIP PARTS**

Qty	Reference	Description	Manufacturer	Part Number
1	U1	HIGH SPEED SYNCHRONOUS BUCK CONTROLLER	Microchip Technology Inc.	MCP19035-AAABE/MF

**Note 1:** The components listed in this Bill of Materials are representative of the PCB assembly. The released BOM used in manufacturing uses all RoHS-compliant components.

**TABLE B-3: BILL OF MATERIALS (BOM) – MECHANICAL PARTS**

Qty	Reference	Description	Manufacturer	Part Number
4	PAD1, PAD2, PAD3, PAD4	MECH HW RUBBER PAD BUMPON HEMISPHERE 0.44" X 0.20" BLACK	3M	SJ-5003 (BLACK)

**Note 1:** The components listed in this Bill of Materials are representative of the PCB assembly. The released BOM used in manufacturing uses all RoHS-compliant components.


**Appendix C. Typical Performance Data, Curves and Waveforms**

**C.1 INTRODUCTION**

This chapter shows some of the typical performance parameters and curves of the MCP19035 300 kHz Synchronous Buck Controller Evaluation Board.

**TABLE C-1: CONVERTER PARAMETERS**

Parameter	Value	Comments
Input Voltage Range (V)	8 - 14	
Output Voltage (V)	1.8	±2.5% tolerance
Maximum Output Current (A)	15	Steady State output current
Output Voltage Ripple (mV)	<30	$V_{IN} = 12V, I_{OUT} = 15A$
Input Voltage Ripple (mV)	<300	$V_{IN} = 12V, I_{OUT} = 15A$
Output Voltage Overshoot during Step Load (mV)	<100	Step Load 0A to 5A
Switching Frequency (kHz)	250 – 350	Typical 300 kHz



**FIGURE C-1:** Efficiency.

# Typical Performance Data, Curves and Waveforms




FIGURE C-2: Load Regulation ( $V_{IN} = 12V$ ).






FIGURE C-3: Output Voltage Ripple/Noise ( $V_{IN} = 12V$ ,  $I_{OUT} = 10A$ ,  $BW = 20$  MHz).

# Typical Performance Data, Curves and Waveforms




**FIGURE C-4:** Input Voltage Ripple/Noise ( $V_{IN} = 12V$ ,  $I_{OUT} = 10A$ ,  $BW = 20\text{ MHz}$ ).




**FIGURE C-5:** SW (TP11), LDRV (TP10) and HDRV (TP9) signals ( $V_{IN} = 12V$ ,  $I_{OUT} = 10A$ ,  $BW = 300\text{ MHz}$ ).

# Typical Performance Data, Curves and Waveforms




**FIGURE C-6:** LDRV (TP10) and HDRV (TP9) signals ( $V_{IN} = 12V$ ,  $I_{OUT} = 10A$ ,  $BW = 300\text{ MHz}$ ).




**FIGURE C-7:** Dead Times 1 ( $V_{IN} = 12V$ ,  $I_{OUT} = 1A$ ,  $BW = 300\text{ MHz}$ ).

# Typical Performance Data, Curves and Waveforms



**FIGURE C-8:** Dead Times 2 ( $V_{IN} = 12V$ ,  $I_{OUT} = 1A$ ,  $BW = 300\text{ MHz}$ ).



**FIGURE C-9:** The Body Diode Conduction Time ( $V_{IN} = 12V$ ,  $I_{OUT} = 10A$ ,  $BW = 300\text{ MHz}$ ).

# Typical Performance Data, Curves and Waveforms




FIGURE C-10: Step Load 1 ( $V_{IN} = 12V$ ).




FIGURE C-11: Step Load 2 ( $V_{IN} = 12V$ ).



# Typical Performance Data, Curves and Waveforms




FIGURE C-12: Power Good Signal (PGOOD).




FIGURE C-13: Soft Start.



# MICROCHIP

## Worldwide Sales and Service

### AMERICAS

**Corporate Office**  
2355 West Chandler Blvd.  
Chandler, AZ 85224-6199  
Tel: 480-792-7200  
Fax: 480-792-7277  
Technical Support:  
<http://www.microchip.com/support>  
Web Address:  
[www.microchip.com](http://www.microchip.com)

#### Atlanta

Duluth, GA  
Tel: 678-957-9614  
Fax: 678-957-1455

#### Austin, TX

Tel: 512-257-3370

#### Boston

Westborough, MA  
Tel: 774-760-0087  
Fax: 774-760-0088

#### Chicago

Itasca, IL  
Tel: 630-285-0071  
Fax: 630-285-0075

#### Dallas

Addison, TX  
Tel: 972-818-7423  
Fax: 972-818-2924

#### Detroit

Novi, MI  
Tel: 248-848-4000

#### Houston, TX

Tel: 281-894-5983

#### Indianapolis

Noblesville, IN  
Tel: 317-773-8323  
Fax: 317-773-5453  
Tel: 317-536-2380

#### Los Angeles

Mission Viejo, CA  
Tel: 949-462-9523  
Fax: 949-462-9608  
Tel: 951-273-7800

#### Raleigh, NC

Tel: 919-844-7510

#### New York, NY

Tel: 631-435-6000

#### San Jose, CA

Tel: 408-735-9110  
Tel: 408-436-4270

#### Canada - Toronto

Tel: 905-695-1980  
Fax: 905-695-2078

### ASIA/PACIFIC

**Australia - Sydney**  
Tel: 61-2-9868-6733

**China - Beijing**  
Tel: 86-10-8569-7000

**China - Chengdu**  
Tel: 86-28-8665-5511

**China - Chongqing**  
Tel: 86-23-8980-9588

**China - Dongguan**  
Tel: 86-769-8702-9880

**China - Guangzhou**  
Tel: 86-20-8755-8029

**China - Hangzhou**  
Tel: 86-571-8792-8115

**China - Hong Kong SAR**  
Tel: 852-2943-5100

**China - Nanjing**  
Tel: 86-25-8473-2460

**China - Qingdao**  
Tel: 86-532-8502-7355

**China - Shanghai**  
Tel: 86-21-3326-8000

**China - Shenyang**  
Tel: 86-24-2334-2829

**China - Shenzhen**  
Tel: 86-755-8864-2200

**China - Suzhou**  
Tel: 86-186-6233-1526

**China - Wuhan**  
Tel: 86-27-5980-5300

**China - Xian**  
Tel: 86-29-8833-7252

**China - Xiamen**  
Tel: 86-592-2388138

**China - Zhuhai**  
Tel: 86-756-3210040

### ASIA/PACIFIC

**India - Bangalore**  
Tel: 91-80-3090-4444

**India - New Delhi**  
Tel: 91-11-4160-8631

**India - Pune**  
Tel: 91-20-4121-0141

**Japan - Osaka**  
Tel: 81-6-6152-7160

**Japan - Tokyo**  
Tel: 81-3-6880-3770

**Korea - Daegu**  
Tel: 82-53-744-4301

**Korea - Seoul**  
Tel: 82-2-554-7200

**Malaysia - Kuala Lumpur**  
Tel: 60-3-7651-7906

**Malaysia - Penang**  
Tel: 60-4-227-8870

**Philippines - Manila**  
Tel: 63-2-634-9065

**Singapore**  
Tel: 65-6334-8870

**Taiwan - Hsin Chu**  
Tel: 886-3-577-8366

**Taiwan - Kaohsiung**  
Tel: 886-7-213-7830

**Taiwan - Taipei**  
Tel: 886-2-2508-8600

**Thailand - Bangkok**  
Tel: 66-2-694-1351

**Vietnam - Ho Chi Minh**  
Tel: 84-28-5448-2100

### EUROPE

**Austria - Wels**  
Tel: 43-7242-2244-39  
Fax: 43-7242-2244-393

**Denmark - Copenhagen**  
Tel: 45-4485-5910  
Fax: 45-4485-2829

**Finland - Espoo**  
Tel: 358-9-4520-820

**France - Paris**  
Tel: 33-1-69-53-63-20  
Fax: 33-1-69-30-90-79

**Germany - Garching**  
Tel: 49-8931-9700

**Germany - Haan**  
Tel: 49-2129-3766400

**Germany - Heilbronn**  
Tel: 49-7131-72400

**Germany - Karlsruhe**  
Tel: 49-721-625370

**Germany - Munich**  
Tel: 49-89-627-144-0  
Fax: 49-89-627-144-44

**Germany - Rosenheim**  
Tel: 49-8031-354-560

**Israel - Ra'anana**  
Tel: 972-9-744-7705

**Italy - Milan**  
Tel: 39-0331-742611  
Fax: 39-0331-466781

**Italy - Padova**  
Tel: 39-049-7625286

**Netherlands - Drunen**  
Tel: 31-416-690399  
Fax: 31-416-690340

**Norway - Trondheim**  
Tel: 47-7288-4388

**Poland - Warsaw**  
Tel: 48-22-3325737

**Romania - Bucharest**  
Tel: 40-21-407-87-50

**Spain - Madrid**  
Tel: 34-91-708-08-90  
Fax: 34-91-708-08-91

**Sweden - Gothenberg**  
Tel: 46-31-704-60-40

**Sweden - Stockholm**  
Tel: 46-8-5090-4654

**UK - Wokingham**  
Tel: 44-118-921-5800  
Fax: 44-118-921-5820