

General Description


The SLVU2.8-8 is in an SOP-8 package and may be used to protect four high-speed line pairs. The “flow-thru” design minimizes trace inductance and reduces voltage overshoot associated with ESD events. The low clamping voltage of the SLVU2.8-8 minimizes the stress on the protected IC.

Applications

- Ethernet – 10/100/1000 Base T
- WAN/LAN Equipment
- Desktops, Servers, Notebooks & Handhelds, base stations Laser Diode Protection

Features

- 400 W Peak Pulse Power per Line ($t_p=8/20\mu s$)
- Protects four line pairs
- Low capacitance
- Low Leakage Current.
- Low Operating and Clamping Voltages.
- Transient Protection for High Speed Data Lines to
IEC61000-4-2(ESD) ±15kV(air), ±8kV(Contact)
IEC61000-4-4(EFT) 40A(5/50ns)
IEC61000-4-5(lightning) 24A(8/20us)



Absolute Maximum Ratings

Parameter	Symbol	Value	Units
Peak Pulse Power ($t_p = 8/20\mu s$) - See Fig1.	P_{PK}	400	W
Peak Pulse Current ($t_p = 8/20\mu s$)	I_{PP}	24	A
Storage Temperature Range	T_{STG}	-55 to 150	°C
Operating Junction Temperature Range	T_J	-55 to 150	°C




Fig1. Peak Pulse Power VS Pulse Time

Utralow Capacitance Transient Voltage Suppressors Array

Electrical Parameter

Symbol	Parameter
I_{PP}	Peak Pulse Current
V_C	Clamping Voltage @ I_{PP}
V_{RWM}	Reverse Stand-Off Voltage
I_R	Reverse Leakage Current @ V_{RWM}
V_{SB}	Snap-Back Voltage @ I_{SB}
I_{SB}	Snap-Back Current
V_{PT}	Punch-Through Voltage
I_{PT}	Punch-Through Current




Fig2. SLVU2.8-8 IV Characteristic Curve

Electrical Characteristics

Parameter	Symbol	Conditions	Minimum	Typical	Maximum	Units
Reverse Stand-Off Voltage	V_{RWM}				2.8	V
Punch-Through Voltage	V_{PT}	$I_{PT} = 2\mu A$	3.0			V
Snap-Back Voltage	V_{SB}	$I_{SB} = 50mA$	2.8			V
Reverse Leakage Current	I_R	$V_{RWM} = 2.8V, T = 25^\circ C$ (Each Line)			1	μA
Clamping Voltage	V_C	$I_{PP} = 2A, t_p = 8/20\mu s$ (Each Line)			5.5	V
Clamping Voltage	V_C	$I_{PP} = 5A, t_p = 8/20\mu s$ (Each Line)			8.5	V
Clamping Voltage	V_C	$I_{PP} = 24A, t_p = 8/20\mu s$ (Each Line)			15	V
Junction Capacitance	C_j	$V_R = 0V, f = 1MHz$ (Each Line)		7	10	pF

Typical Characteristics




Fig3. Pulse Waveform




Fig4. Power Derating Curve




Fig5. Clamping Voltage vs. Peak Pulse Current




Fig6. Forward Voltage vs. Forward Current




Fig7. Insertion Loss S21

Application Note

Electronic equipment is susceptible to damage caused by Electrostatic Discharge (ESD), Electrical Fast Transients (EFT), and tertiary lightning effects. Knowing that equipment can be damaged, the SLVU2.8-4 was designed to provide the level of protection required to safe guard sensitive equipment. This product can be used in different configurations to provide a level of protection to meet unidirectional line requirements as well as bidirectional requirements either in a common-mode or differential-mode configuration.

Ultralow Capacitance Transient Voltage Suppressors Array

Bidirectional Common-Mode Protection (Figure 9)

The SLVU2.8-8 provides up to four lines of protection in a common-mode configuration as depicted in figure 9.

Circuit connectivity is as follows:

- Line 1 is connected to Pin 1
- Line 2 is connected to Pin 7
- Line 3 is connected to Pin 3
- Line 4 is connected to Pin 5
- Pins 2, 4, 7 and 8 are connected to ground




Fig 9.

Bidirectional different-Mode Protection (Figure 10)

The SLVU2.8-8 provides up to two-line pairs of protection in a differential-mode configuration as depicted in figure 11.

Circuit connectivity is as follows:

- Line Pair 1 is connected to Pins 1 & 2
- Line Pair 2 is connected to Pins 3 & 4
- Line Pair 3 is connected to Pins 7 & 8
- Line Pair 4 is connected to Pins 5 & 6




Fig10.

Circuit Board Layout Protection

Circuit board layout is critical for Electromagnetic Compatibility (EMC) protection. The following guidelines are recommended:

- The protection device should be placed near the input terminals or connectors, the device will divert the transient current immediately before it can be coupled into the nearby traces.
- The path length between the TVS device and the protected line should be minimized.
- All conductive loops including power and ground loops should be minimized.
- The transient current return path to ground should be kept as short as possible to reduce parasitic inductance.
- Ground planes should be used whenever possible. For multilayer PCBs, use ground vias.

Typical Applications




Fig11. Gigabit Ethernet Protection Circuit

Typical Applications





Fig12. One SLVU2.8-8 Protecting Two 10/100 Ethernet Port

SOP-8 MECHANICAL DATA

DIM	Millimeters		
	MIN	TYP	MAX
A			1.75
A1	0.10		0.25
A2	1.35	1.55	1.75
B	0.35	0.42	0.49
C	0.19		0.25
D	4.80	4.90	5.00
E	5.80	6.00	6.20
E1	3.80	3.95	4.00
e		1.27	
L	0.40		0.90
K	0°		8°



IMPORTANT NOTICE

and **SXSEMI**[®] are registered trademarks of **SXSEMI Electronics Co., Ltd** (SXSEMI), SXSEMI reserves the right to make changes without further notice to any products herein. SXSEMI makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SXSEMI assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SXSEMI data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SXSEMI does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.