

Dual Bench DC Power Supply



Features:

- Complete digital control
- 10mV / 1mA resolution
- Low noise and ripple
- CV / CC constant voltage and constant current mode
- OCP and OVP settings, constant protection mode
- 5 sets of parameters can be stored and recalled
- Output switch control
- Power-off memory function
- Keyboard lock function

Specifications:

Voltage Range / Current Range	0 - 30V / 0 - 3A × 2
Load Regulation	Voltage : ≤0.01% +4mV / Current : ≤0.02% +5mA
Line Regulation	Voltage : ≤0.01% +3mV / Current : ≤0.01% +3mA
Setup Resolution	Voltage : 10mV / Current : 1mA
Setup Accuracy (25°C ±5°C)	Voltage : ≤0.5% +20mV / Current : ≤0.5% +5mA
Ripple (20Hz - 20MHz)	Voltage : ≤ 1mVrms / Current : ≤ 3mArms
Temp. Coefficient	Voltage : ≤0.1% +10mV / Current : ≤0.1% +5mA
Read Back Accuracy	Voltage : 10mV / Current : 1mA
Read Back Temp. Coefficient	Voltage : ≤100ppm +10mV / Current : ≤ 100ppm +5mA
Reaction Time (10% Rated load)	Voltage Rise : ≤ 100mS / Voltage Drop : ≤ 100mS (10% Rated load)
Operation Environment	Indoor use Altitude : ≤ 2,000m Ambient temperature : 0°C ~ 40°C Relative humidity : ≤ 80%
Weight and Dimension	7kg / 220mm(W) × 280mm(H) × 160mm(D)
Storage Environment	Ambient temperature : -10°C ~ +70°C Relative humidity : ≤ 70%
Accessories	User manual, UK Power cord (1.2m), Euro Power Cord (1.2m)

Note: Input Voltage : 230V ±10%

Part Number Table

Description	Part Number
DC Power Supply, Bench, Dual, 3A, 30V	72-10500

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.

