

RADIAL CHOKE COILS / RC TYPE

FEATURES


- ◆ High rated current for high current circuits. Designed by special lead wire to prevent open circuit failure.
- ◆ Low cost with rugged reliability and performance fixed inductor.



APPLICATIONS


- ◆ Excellent as DC-DC converter boost or buck inductors. Also used for filtering applications.

ORDERING CODE




SHAPES

(WITHOUT TUBE)



(WITH UL TUBE)



DIMENSIONS UNIT: mm (WITH ULTUBE)

Part No.	A (Max)	B (Max)	C (Min)	D (Typ)	E (Ref.)
RC 0406	5.5	8.0	10	0.50	2.6
RC 0608	7.5	10.0	10	0.60	2.6
RC 0810	10.5	12.5	10	0.65	5.0
RC 0912	11.5	14.0	10	0.80	5.0
RC 1012	11.5	14.0	10	0.80	6.0
RC 1016	12.0	18.0	10	0.80	7.0

*DESIGN AS CUSTOMER'S REQUESTED SPECIFICATIONS



CORE MASTER ENTERPRISE CO., LTD.

<http://www.coremaster.com.tw>