



## 快恢复整流二极管 Fast Recovery Rectifier Diode


## ■ 特征 Features

- $I_o$  1.0A
- $V_{RRM}$  50V-1000V
- 耐正向浪涌电流能力高  
High surge current capability
- 封装：模压塑料  
Cases: Molded plastic

## ■ 用途 Applications

- 整流用 Rectifier

## ■ 外形尺寸和印记 Outline Dimensions and Mark



## ■ 极限值 (绝对最大额定值)

## Limiting Values (Absolute Maximum Rating)

参数名称 Item	符号 Symbol	单位 Unit	测试条件 Test Conditions	GR1						
				A	B	D	G	J	K	M
反向重复峰值电压 Repetitive Peak Reverse Voltage	$V_{RRM}$	V		50	100	200	400	600	800	1000
正向平均电流 Average Forward Current	$I_{F(AV)}$	A	正弦半波 60Hz, 电阻负载, $T_L=90^\circ\text{C}$ 60Hz Half-sine wave, Resistance load, $T_L=90^\circ\text{C}$							1.0
正向(不重复)浪涌电流 Surge(Non-repetitive)Forward Current	$I_{FSM}$	A	正弦半波 60Hz, 一个周期, $T_a=25^\circ\text{C}$ 60Hz Half-sine wave, 1 cycle, $T_a=25^\circ\text{C}$							30
结温 Junction Temperature	$T_J$	$^\circ\text{C}$								-55~+150
储存温度 Storage Temperature	$T_{STG}$	$^\circ\text{C}$								-55 ~ +150

■ 电特性 ( $T_a=25^\circ\text{C}$  除非另有规定)Electrical Characteristics ( $T_a=25^\circ\text{C}$  Unless otherwise specified)

参数名称 Item	符号 Symbol	单位 Unit	测试条件 Test Condition	GR1						
				A	B	D	G	J	K	M
正向峰值电压 Peak Forward Voltage	$V_F$	V	$I_F=1.0\text{A}$							1.3
最大反向恢复时间 Maximum reverse recovery time	$t_{rr}$	ns	$I_F=0.5\text{A}, I_R=1.0\text{A}, I_{rr}=0.25\text{A}$			150		250		500
反向漏电流 Peak Reverse Current	$I_{RRM1}$	$\mu\text{A}$	$V_{RM}=V_{RRM}$	$T_a=25^\circ\text{C}$						5
	$I_{RRM2}$			$T_a=125^\circ\text{C}$						50
热阻(典型) Thermal Resistance(Typical)	$R_{\theta J-A}$	$^\circ\text{C}/\text{W}$	结和环境之间 Between junction and ambient							105 <sup>1)</sup>
	$R_{\theta J-L}$		结和终端之间 Between junction and terminal							32 <sup>1)</sup>

## 备注：Notes:

<sup>1)</sup> 热阻从结到环境及从结到引线，在电路板的0.2" x 0.2" (5.0毫米 x 5.0毫米)铜垫片区

Thermal resistance from junction to ambient and from junction to lead mounted on P.C.B. with 0.2" x 0.2" (5.0 mm x 5.0 mm) copper pad areas



## ■特性曲线(典型) Characteristics(Typical)







图5: 反向恢复时间试验电路及测试波形示意图  
FIG.5: Diagram of circuit and Testing wave form of reverse recovery time

