

4V Drive Nch MOSFET

RSD050N10

●Structure

Silicon N-channel MOSFET

● Features

- 1) Low on-resistance.
- 2) Fast switching speed.
- 3) Drive circuits can be simple.
- 3) Parallel use is easy.

Applications

Switching

Packaging specifications

	<u> </u>		
	Package	CPT3	
Type	Code	TL	
	Basic ordering unit (pieces)	2500	

● Absolute maximum ratings (T_a=25°C)

Parameter		Symbol	Limits	Unit
Drain-source voltage		V_{DSS}	100	V
Gate-source voltage		V_{GSS}	±20	V
Drain current	Continuous	I _D	±5.0	Α
	Pulsed	I _{DP} *1	±20	Α
Source current	Continuous	I _S	5.0	Α
(Body Diode)	Pulsed	I _{SP} *1	20	Α
Power dissipation		P _D *2	15	W
Channel temperature		T _{ch}	150	°C
Range of storage temperature		T _{stq}	-55 to +150	°C


^{*1} Pw≦10μs, Duty cycle≦1%

●Thermal resistance


Parameter	Symbol	Limits	Unit
Channel to Case	R _{th (ch-c)} *	8.33	°C / W

^{*} T_c=25°C

●Dimensions (Unit: mm)



●Inner circuit



^{*2} T_c=25°C

●Electrical characteristics (T_a=25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Gate-source leakage	I_{GSS}	-	-	±10	μΑ	$V_{GS}=\pm20V, V_{DS}=0V$
Drain-source breakdown voltage	$V_{(BR)DSS}$	100	1	-	>	$I_D=1$ mA, $V_{GS}=0$ V
Zero gate voltage drain current	I _{DSS}	1	-	10	μΑ	V _{DS} =100V, V _{GS} =0V
Gate threshold voltage	V _{GS (th)}	1.0	-	2.5	V	$V_{DS}=10V$, $I_{D}=1mA$
Otatia duain accusa an atata	*	1	135	190	mΩ	I _D =5.0A, V _{GS} =10V
Static drain-source on-state resistance	R _{DS (on)}	1	142	200		I _D =5.0A, V _{GS} =4.5V
resistance		-	145	205		I _D =5.0A, V _{GS} =4.0V
Forward transfer admittance	ΙΥ _{fs} Γ*	2.5	-	-	S	I _D =5.0A, V _{DS} =10V
Input capacitance	C _{iss}	-	530	-	pF	V _{DS} =25V
Output capacitance	C _{oss}	-	50	-	pF	V _{GS} =0V
Reverse transfer capacitance	C_{rss}	-	30	-	pF	f=1MHz
Turn-on delay time	t _{d(on)} *	-	10	-	ns	I _D =2.5A, V _{DD} ≒. 50V
Rise time	t _r *	1	15	-	ns	V _{GS} =10V
Turn-off delay time	t _{d(off)} *	-	45	-	ns	$R_L=20\Omega$
Fall time	t _f *	-	15	-	ns	$R_G=10\Omega$
Total gate charge	Q _g *	-	14	-	nC	V _{DD} ≒ 50V
Gate-source charge	Q _{gs} *	-	1.7	-	nC	I _D =5.0A,
Gate-drain charge	Q _{gd} *	-	3.0	-	nC	V _{GS} =10V

^{*}Pulsed

●Body diode characteristics (Source-Drain) (T_a=25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Forward Voltage	V _{SD} *	-	-	1.2	V	I _s =5.0A, V _{GS} =0V

^{*}Pulsed

●Electrical characteristic curves (T_a=25°C)




Fig.3 Static Drain-Source On-State Resistance vs. Drain Current




Fig.5 Static Drain-Source On-State Resistance vs. Drain Current




Fig.2 Typical Output Characteristics (II)




Fig.4 Static Drain-Source On-State Resistance vs. Drain Current





Fig.6 Static Drain-Source On-State Resistance vs. Drain Current



Source Current: Is [A]

Switching Time : t [ns]

Fig.7 Forward Transfer Admittance vs. Drain Current




Fig.9 Source Current vs. Source-Drain Voltage




Fig.11 Switching Characteristics




Fig.8 Typical Transfer Characteristics




Fig.10 Static Drain-Source On-State Resistance vs. Gate-Source Voltage





Fig.12 Dynamic Input Characteristics



Normalized Transient Thermal Resistance : r(t)

Fig.13 Typical Capacitance vs. Drain-Source Voltage




Fig.14 Maximum Safe Operating Area





Fig.15 Normalized Transient Thermal Resistance v.s. Pulse Width



www.rohm.com © 2012 ROHM Co., Ltd. All rights reserved.

● Measurement circuits




Fig.1-1 Switching time measurement circuit




Fig.2-1 Gate charge measurement circuit




Fig.1-2 Switching waveforms




Fig.2-2 Gate Charge Waveform

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.



Thank you for your accessing to ROHM product informations. More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

http://www.rohm.com/contact/