

Speaker transformers for vacuum-tube amplifiers, TGL series



Transformer type speaker

Symbol	Power [VA]	Transmission band frequency [kHz]	Primary winding imp. [k Ω]	Sec. winding imped. [Ω]	Transformation ratio
TGL5/001	5	0.04...20	5.2	8	0,0366
TGL5/002	5	0.04...20	5.2	4	0,0256
TGL15/001	15	0.02...20	1	8	0,085
TGL20/001	20	0.05...12	3.2	8	0,0504
TGL20/002	20	0.03...15	10	8	0,0282
TGL20/003	20	0.02...20	1.13	8	0,0839
TGL35/001	35	0.035...20	1.73	4	0,048
TGL35/002	35	0.035...20	1.73	8	0,068
TGL35/003	35	0.02...20	0.85	4	0,068
TGL40/001	40	0.04...16	4	8	0,0445
TGL60/001	60	0.05...12	3	4	0,036
TGL60/002	60	0.04...15	2.2	8	0,06
TGL60/003	60	0.04...15	2.2	4	0,043
TGL80/001	80	0.05...12	0.77	4	0,0716