# DATASHEET

# 6 PIN DIP RANDOM-PHASE TRIAC DRIVER PHOTOCOUPLER EL301X, EL302X, EL305X Series

EVERLIGH



#### Features:

- Peak breakdown voltage
- 250V: EL301X
- 400V: EL302X
- 600V: EL305X
- High isolation voltage between input and output (Viso=5000 V rms)
- Compact dual-in-line package
- Pb free and RoHS compliant.
- UL approved (No. E214129)
- VDE approved (No.132249)
- SEMKO approved
- NEMKO approved
- DEMKO approved
- FIMKO approved
- CSA approved

#### Description

The EL301X, EL302X and EL305X series of devices each consist of a GaAs infrared emitting diode optically coupled to a monolithic silicon random phase photo Triac.

They are designed for interfacing between electronic controls and power triacs to control resistive and inductive loads for 115 to 240 VAC operations.

## Applications

- Solenoid/valve controls
- Lamp ballasts
- Static AC power switch
- Interfacing microprocessors to 115 to 240Vac peripherals
- Incandescent lamp dimmers
- Temperature controls
- Motor controls





#### Pin Configuration

- 1. Anode
- 2. Cathode
- 3. No Connection
- 4. Terminal
- 5. Substrate (do not connect)
- 6. Terminal

# Absolute Maximum Ratings (Ta=25℃)

|                                     | Parameter                               |                        | Symbol              | Rating | Unit          |
|-------------------------------------|---|------------------------|---------------------|--------|---------------|
| Input                               | Forward current                         |                        | ١ <sub>F</sub>      | 60     | mA            |
|                                     | Reverse voltage                         |                        | V <sub>R</sub>      | 6      | V             |
|                                     | Power dissipation                       |                        | <b>D</b>            | 100    | mW            |
|                                     | Derating factor (above                  | T <sub>a</sub> = 85°C) | P <sub>D</sub> -    | 3.8    | mW /℃         |
| Output                              |   | EL301X                 |                     | 250    |               |
|                                     | Off-state Output<br>Terminal Voltage    | EL302X                 | V <sub>DRM</sub>    | 400    | V             |
|                                     |   | EL305X                 |                     | 600    | _             |
|                                     | Peak Repetitive Surge (pw=100µs,120pps) | Current                | I <sub>TSM</sub>    | 1      | А             |
|                                     | On-State RMS Current                    |                        | I <sub>T(RMS)</sub> | 100    | mA            |
|                                     | Power dissipation                       |                        | <b>D</b>            | 300    | mW            |
|                                     | Derating factor (above                  | T <sub>a</sub> = 85°C) | P <sub>C</sub> -    | 7.4    | <b>mW</b> /°℃ |
| Total power dissipation             |   | P <sub>TOT</sub>       | 330                 | mW     |               |
| Isolation voltage <sup>*1</sup>     |   | V <sub>ISO</sub>       | 5000                | Vrms   |               |
| Operating temperature               |   | T <sub>OPR</sub>       | -55 to 100          | °C     |               |
| Storage temperature                 |   | T <sub>STG</sub>       | -55 to 125          | °C     |               |
| Soldering Temperature* <sup>2</sup> |   |                        | T <sub>SOL</sub>    | 260    | °C            |

Notes:

\*1 AC for 1 minute, R.H.= 40 ~ 60% R.H. In this test, pins 1, 2&3 are shorted together, and pins 4, 5 & 6 are shorted together. \*2 For 10 seconds

# Electro-Optical Characteristics (Ta=25°C unless specified otherwise)

| Input                                   |                  |      |       |      |           |  |
|---|------------------|------|-------|------|-----------|--|
| Parameter                               | Symbol           | Min. | Typ.* | Max. | Unit      | Condition  |
| Forward Voltage                         | V <sub>F</sub>   | -    | 1.18  | 1.5  | V         | I <sub>F</sub> = 10mA  |
| Reverse Leakage current                 | I <sub>R</sub>   | -    | -     | 10   | μΑ        | $V_R = 6V$   |
| Output                                  |                  |      |       |      |           |  |
| Parameter                               | Symbol           | Min. | Тур.* | Max. | Unit      | Condition  |
| Peak Blocking Current                   | I <sub>DRM</sub> | -    | -     | 100  | nA        | $V_{DRM}$ = Rated $V_{DRM}$<br>I <sub>F</sub> = 0mA                                  |
| Peak On-state Voltage                   | $V_{TM}$         | -    | -     | 2.5  | V         | I <sub>™</sub> =100mA peak,<br>I <sub>F</sub> =Rated I <sub>FT</sub>                 |
| Critical Rate of EL301X                 |                  | -    | 100   | -    |           | V <sub>PEAK</sub> =Rated V <sub>DRM</sub> ,  |
| Rise off-state EL302X<br>Voltage EL305X | uv/ut            | 1000 | -     | -    | V/μs<br>- | I <sub>F</sub> =0 (Fig. 8)<br>V <sub>PEAK</sub> =400V,<br>I <sub>F</sub> =0 (Fig. 8) |

#### **Transfer Characteristics**

| Parameter              |                            | Symbol               | Min. | Тур.* | Max. | Unit | Condition                |
|------------------------|----------------------------|----------------------|------|-------|------|------|--------------------------|
|                        | EL3020                     |                      |      |       | 30   |      |                          |
| LED Trigger<br>Current | EL3010<br>EL3021<br>EL3051 |                      | -    | -     | 15   | mA   | Main terminal Voltage=3V |
|                        | EL3011<br>EL3022<br>EL3052 | -<br>I <sub>FT</sub> | -    | -     | 10   |      |                          |
|                        | EL3012<br>EL3023<br>EL3053 |                      | -    | -     | 5    |      |                          |
| Holding Curren         | t                          | Ι <sub>Η</sub>       | -    | 250   | -    | μΑ   |                          |

\* Typical values at  $T_a = 25 \,^{\circ}C$ 

# **Typical Electro-Optical Characteristics Curves**









Figure 4. LED Current Required to Trigger vs. LED Pulse Width







Figure 8. Static dv/dt Test Circuit & Waveform



#### **Measurement Method**

The high voltage pulse is set to the required V<sub>PEAK</sub> value and applied to the D.U.T. output side through the RC circuit above. LED current is not applied. The waveform V<sub>T</sub> is monitored using a x100 scope probe. By varying R<sub>TEST</sub>, the dv/dt (slope) is increased, until the D.U.T. is observed to trigger (waveform collapses). The dv/dt is then decreased until the D.U.T. stops triggering. At this point,  $\tau_{RC}$  is recorded and the dv/dt calculated.

$$dv/dt = \frac{0.632 \times V_{PEAK}}{\tau_{RC}}$$

For example,  $V_{PEAK}$  = 400V for EL302X series. The dv/dt value is calculated as follows:

$$dv/dt = \frac{0.63 \times 400}{\tau_{RC}} = \frac{252}{\tau_{RC}}$$

**EVERLIGHT** 

# **Order Information**

#### **Part Number**



#### Note

- X = Part No. for EL301x (0, 1 or 2)
- X = Part No. for EL302x, EL305x (1, 2 or 3)
- Y = Lead form option (S, S1, M or none)
- Z = Tape and reel option (TA, TB or none).
- V = VDE safety approved (optional)

| Option  | Description   | Packing quantity    |
|---------|---|---------------------|
| None    | Standard DIP-6  | 65 units per tube   |
| М       | Wide lead bend (0.4 inch spacing)                             | 65 units per tube   |
| S (TA)  | Surface mount lead form + TA tape & reel option               | 1000 units per reel |
| S (TB)  | Surface mount lead form + TB tape & reel option               | 1000 units per reel |
| S1 (TA) | Surface mount lead form (low profile) + TA tape & reel option | 1000 units per reel |
| S1 (TB) | Surface mount lead form (low profile) + TB tape & reel option | 1000 units per reel |

# Package Dimension (Dimensions in mm)

## Standard DIP Type





#### **Option M Type**





**EVERLIGHT** 

#### **Option S Type**







#### **Option S1 Type**









## Recommended pad layout for surface mount leadform



## **Device Marking**



#### Notes

| EL   | denotes EVERLIGHT         |
|------|---------------------------|
| 3053 | denotes Device Number     |
| Υ    | denotes 1 digit Year code |
| WW   | denotes 2 digit Week code |
| V    | denotes VDE (optional)    |

# **Tape & Reel Packing Specifications**

**Tape dimensions** 



Direction of feed from reel

#### Option TB



#### Direction of feed from reel



| Dimension No.  | Α        | В       | Do      | D1         | Е        | F       |
|----------------|----------|---------|---------|------------|----------|---------|
| Dimension (mm) | 10.4±0.1 | 7.5±0.1 | 1.5±0.1 | 1.5+0.1/-0 | 1.75±0.1 | 7.5±0.1 |
| 1              | •        |         | •       | -          | -        |         |
|                |          |         |         |            |          |         |
| Dimension No.  | Ро       | P1      | P2      | t          | W        | к       |



### **Precautions for Use**

#### 1. Soldering Condition

1.1 (A) Maximum Body Case Temperature Profile for evaluation of Reflow Profile



Note:

#### Preheat

| Temperature min (T <sub>smin</sub> )        |
|---|
| Temperature max (T <sub>smax</sub> )        |
| Time ( $T_{smin}$ to $T_{smax}$ ) ( $t_s$ ) |
| Average ramp-up rate $(T_{smax} to T_p)$    |

#### Other

| Liquidus Temperature $(T_L)$  | 2 |
|---|---|
| Time above Liquidus Temperature (t $_{L}$ )   | 6 |
| Peak Temperature (T <sub>P</sub> )  | 2 |
| Time within 5 $^{\circ}\!\!\!C$ of Actual Peak Temperature: $T_P$ - 5 $^{\circ}\!\!C$ | ( |
| Ramp- Down Rate from Peak Temperature   | ( |
| Time 25 $^{\circ}$ C to peak temperature  | 8 |
| Reflow times  | 3 |

Reference: IPC/JEDEC J-STD-020D

150 ℃ 200℃ 60-120 seconds 3 ℃/second max

217 ℃ 60-100 sec 260 ℃ 30 s 6 ℃ /second max. 8 minutes max. 3 times

# DISCLAIMER

- 1. Above specification may be changed without notice. EVERLIGHT will reserve authority on material change for above specification.
- 2. When using this product, please observe the absolute maximum ratings and the instructions for using outlined in these specification sheets. EVERLIGHT assumes no responsibility for any damage resulting from use of the product which does not comply with the absolute maximum ratings and the instructions included in these specification sheets.
- 3. These specification sheets include materials protected under copyright of EVERLIGHT corporation. Please don't reproduce or cause anyone to reproduce them without EVERLIGHT's consent.